

# CXT425



# Cobra®

GMRS/FRS TWO-WAY RADIOS



### Up to 25 mile range

Rugged design with extended range capability.

### NOAA weather and emergency radio

Be prepared for storms and emergencies with built-in NOAA radio receiver.

### VOX

Voice-activated transmission frees hands for other tasks.

### 10-channel memory

Store and retrieve up to 10 frequently used channel settings.

### Scan

Easily locate conversations or transmissions in progress.

[www.cobra.com](http://www.cobra.com)



# CXT425

## Features

## Benefits

<b>UHF/FM</b>	Ultra-clear long distance reception.
<b>Up to 25 Mile Range</b>	Extended range capability provides up to 25 mile range. (Range will vary depending on terrain and conditions.)
<b>Selectable Power Output</b>	Choose between High Power to maximize range, or Low Power to conserve battery life (in GMRS)
<b>2662 Channel Combinations</b>	Available when the 22 channels are combined with the 121 privacy codes (38 CTCSS/83 DCS), these combinations prevent interference from other radios.
<b>NOAA Weather and Emergency Radio</b>	Be prepared for storms and emergencies with the built-in NOAA radio receiver providing coverage of all government operated weather channels.
<b>VOX</b>	The user's voice is detected and the radio transmits without the need to press any buttons, freeing hands for other tasks. 5 VOX sensitivity levels allow the user to select at which point the radio will detect their voice.
<b>10 Channel Memory</b>	Allows the user to program up to 10 channel or channel/privacy code combinations for easy retrieval
<b>Battery Saver Circuitry</b>	A unique circuit extends the life of the batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.
<b>Scan Feature</b>	Allows the user to scan either channels or privacy codes within a channel to locate conversations in progress.
<b>Key Lock</b>	When activated, provides key pad security eliminating accidental channel changes.
<b>10 Call Tones</b>	Allows the user to differentiate between up to 10 different parties on incoming calls.
<b>Roger Beep Tone (selectable on/off)</b>	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk. This feature is selectable and can be turned on or off.
<b>Auto Squelch</b>	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
<b>Maximum Range Extender</b>	Overrides Auto Squelch to provide extended range reception.
<b>Illuminated LCD Display</b>	Provides maximum ease of use even at night.
<b>Keystroke Tone Signal (selectable on/off)</b>	Confirms key activation. This feature is selectable and can be turned on or off.
<b>Speaker/Microphone/Charger Jack</b>	Allows use of wall charger, or earphone speaker/microphones (not included) for "hands-free" operation.
<b>Belt Clip</b>	Secures your microTALK® radio while on the go.
<b>1 Year Warranty</b>	On radios sold in the U.S.A.
<b>8 AAA NiMH Rechargeable Batteries</b>	Radios can also be used with 4 AAA alkaline batteries per radio (not included).
<b>Two-Port Desktop Charger</b>	Charges supplied NiMH batteries inside radios. Charger accommodates 1 or 2 radios.

## Unit Specifications - General

<b>Unit Dimension</b>	6.7" x 2.1" x 1.4" (170mm x 54.5mm x 37.2mm)	<b>Master Pack Bar Code</b>	1 00 28377 90898 6	<b>Master Pack Weight</b>	6.06 lbs. (2750 g.)
<b>Unit Weight</b>	3.9 oz. (110g) without batteries	<b>Clamshell Dimension</b>	11.394" x 7.5" x 2.949" (289.4mm x 190.5mm x 74.9mm)	<b>Batteries</b>	4AAA NiMH rechargeable batteries per radio (included) or 4AAA alkaline batteries per radio (not included)
<b>Channels</b>	22 Channels (462.550 MHz-467.7125 MHz)	<b>Clamshell Weight</b>	1.31 lbs. (596 g.)		
<b>SKU#</b>	CXT425	<b>Master Pack Dimension</b>	13.582" x 9.645" x 9.877" (345mm x 245mm x 250.9mm)	<b>Master Pack Qty</b> 4	
<b>UPC</b>	0 28377 90898 9				

\*Specifications subject to change without notice\*

\*All dimensions (H x W x D)\*



\* Packaging is made from recyclable materials.

Cobra, microTALK, Nothing Comes Close to a Cobra, Rewind-Say-Again, VibrAlert and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation is a trademark of Cobra Electronics Corporation, USA.

2009 Cobra Electronics Corporation, 6500 West Cortland Street, Chicago, IL 60707, USA